

# Product datasheet

Specifications



## Ultimate Screwless flat plate - switched socket - 1 gang - brass

GU3410-BPB

⚠ Discontinued on: 23 Jul 2025

⚠ Discontinued

### Main

Range	Ultimate
Aesthetic name	Screwless flat plate
Product or component type	Switched socket
Device application	Power supply
fixing mode	By screws
Socket number	1
Switch function	1-pole 1-way
Outlet poles configuration	2P + E
Colour tint	Brass Black
Rated current	13 A

### Complementary

Device presentation	Complete product
Device mounting	Flush
Actuator	Rocker
Number of rocker	1
Outlet standard	BS 1363
Outlet standard deviation	British
Earth circuit	Standard earth
Surface finish	Polished
Material	Steel
[Ue] rated operational voltage	230 V
Network type	AC
Network frequency	50/60 Hz
Connections - terminals	Screw terminal
IP degree of protection	IP20
Width	88 mm
Height	88 mm
Depth	30 mm

Excluding VAT, FCA Jabal Ali & are subject to change – check with your local distributor.

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

# Packing Units


Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	8.8 cm
Package 1 Width	8.8 cm
Package 1 Length	3 cm
Package 1 Weight	0.001 g

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.



[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Use Better

 Materials and Substances	
Packaging made with recycled cardboard	Yes
Packaging without single use plastic	No
<a href="#">EU RoHS Directive</a>	Compliant with Exemptions

Use Again

 Repack and remanufacture	
Take-back	No
WEEE Label	 The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins